



## AB-350K

- AB-350K is a small and smart sprocket printer.
- Its typical feature is print two copies press sensor paper. It is suitable to be used in pin card and several kinds of recreational machines to print passwords.

### AB-350K Sprocket Printer

- Adjustable 76mm and 89mm sprocket paper.
- Double copies or multi-copies printing.
- Especially suitable used in telecom passwords card and recharging card printing.

### Features




### Technical specifications

Printing method	Serial impact dot matrix
Number of head pin	9 wires
Printing direction	Bi-directional
Line per second	Approx. 4LPS
Characters per line	40(7×9)
Ribbon type	Disable
Paper type	Sprocket paper
Paper width	76mm ±0.5mm 89mm ±0.5mm
Thickness	0.05mm~0.095mm
Data buffer	4K bytes
Power adapter	DC 24V, 2A
Power consumption	Standby: 8W Operation: 24W
Reliability	Printer MCBF: 5,000,000 lines Print head life: 8,000,000 lines
Operation temperature	0°C~40°C(32 ~104 )
Operation humidity	30%~80%
Storage temperature	-5°C~50°C(32 ~122 )
Storage humidity	10%~95%

A. Put the sprocket paper into the slot. Be sure that the gear block stick to the paper's hole.



B. Turn the paper loading knob in the clockwise direction. Until the paper is suitable.



### AB-350K Sprocket Printer

- Adjustable 76mm and 89mm sprocket paper.
- Double copies or multi-copies printing.
- Especially suitable used in telecom passwords card and recharging card printing.

